

ST

Technical Data Sheet

VA315

Clamp Meter

Auto range 1000 Amps



Application

The meter is an autorange professional clamp meter for measuring DC and AC voltage, AC current, Resistance, Capacitance, Frequency, ADP, Diode, and Continuity Test with battery operated.

There is the AC measurement to be RMS or TRUE RMS about the meter. It is chosen as user buy.

Product Features

Max.Display	5999
LCD Size	44x23 mm
Max.Jaw Opening	φ 40 mm
Continuity test	√
Auto range	√
Auto/Manual range	√
Data hold	√
True RMS Measurement	√
Relative Measurement	-
Max/Min Value Measurement	√
Back light	√
Auto power off	√
Low Power Indication	-
Diode test	√
Bar graph	-
Power	1.5V battery (AAA)X3
Size	225x86x32 mm
Weight	~ 330g (including battery)

Product Specifications

DC Voltage	6V/60V/600V± (0.8% +5) 1000V ± (1%+2)
AC Voltage	6V/60V/600V/700V±(1.2%+5)
DC Current	-
AC Current	600A±2 (2.5%+5) 1000A± (3%+5)
Resistance	600/6K/60K/600K/6MΩ±(1%+3) 60MΩ±(5%+5)
Capacitance	600nF/6μF/60μF/600μF/1000 μF±(4%+5)
Frequency	40/600/6K/60K/100KHZ±(0.1%+2)
Frequency from Clamp	-
ADP Measurement	600mV±(3%+5)
Temperature	-



Sifam Tinsley Instrumentation Ltd

1 Warner Drive, Springwood Industrial Estate,
Braintree, Essex CM7 2YW

Contact No. : +44 (0) 1376 335271

Email: sales@sifamtinsley.com

www.sifamtinsley.co.uk