

DIGITAL MULTIMETER BENCHTOP MULTIMETER **MAS830L3**



The MAS830L3 is a completely portable meter comes with an LCD and a 3.5 digits multimeter. Designed for use by electricians, technicians, servicemen and hobbyists who require an instrument that is accurate, reliable, and always ready for use.

FEATURES

- True RMS Measurement
- Max/ Min Measurement
- Relative Measurement
- Continuity Buzzer
- Peak Hold







SPECIFICATIONS

See the tables below for product specifications.




Product Specifications			
AC Voltage	1000V	Capacitance	60mF
DC Voltage	1000V	Frequency	6MHz
AC Current	10A	Display Counts	6000
DC Current	10A		
Resistance	60MΩ		

* Subject to change without notification.


















CONTENTS

	L145 x W73 x D38mm L5.7" x W2.9" x D1.5" 240g/ 0.53lb		Battery 9V 6F22 x 1
	Test Leads Battery		User Manual

PACKAGING INFORMATION

	Color Box L 100 X W 45 X H 165mm		
	Carton Box 49 X 35.5 X 23cm		X 40Pcs

MAIN APPLICATIONS

						
Domestic	V _{DC}	V _{AC}	A _{AC}	R		
						
Industrial	V _{AC}	V _{AC}	R			
						
Electronics	V _{AC}	V _{AC}	A _{DC}	R		▶