

DIGITAL MULTIMETER INSULATION MULTIMETER VA588



TRMS
Insulation Test

VA588 handheld true RMS insulation Multimeter combine the features of a digital multimeter and insulataion resistance tester.

FEATURES

- True RMS Measurement
- Max/ Min Measurement
- Overload Protection
- Continuity Buzzer
- Back Light



SPECIFICATIONS

See the tables below for product specifications.

Product Specifications			
AC Voltage	1000V	Capacitance	1000 μ F
DC Voltage	1000V	Frequency	2MHz
AC Current	500mA	Display Counts	5000
DC Current	500mA	Insulation Test	0.05M Ω ~2G Ω
Resistance	50M Ω	Temperature	-50 $^{\circ}$ C~1000 $^{\circ}$ C

* Subject to change without notification.

CONTENTS

	L200 x W100 x D40mm L7.9"x W3.9"x D1.6" 560g/ 1.23lb		Battery 1.5V AAA x 6
	Test Leads K-type Thermocouple Carry Bag Battery		User Manual

PACKAGING INFORMATION

	Color Box L 180 X W 80 X H 245mm
	Carton Box 42 X 40 X 27cm
	X 10Pcs

MAIN APPLICATIONS

		V \dots V \sim
		V \dots V \sim R $^{\circ}$ C
		V \dots V \sim A \approx R